

This document must be retained for future reference.

It is the responsibility of the person installing the electrical equipment to ensure that the installation meets the requirements of the IET wiring regulations and is therefore 'fit for purpose'. Factors such as correct selection of components, cable sizing, protective devices and Earth bonding are all critical and should be checked prior to full testing and power-up. Any other regulations applicable to the equipment being installed such as the Machinery Directive and current health and safety legislation must also be adhered to.

All connections (including factory made) must be checked for the correct tightness prior to commissioning of the electrical installation. All connections should also be inspected periodically to ensure correct tightness.

DO NOT USE POWER TOOLS ON THESE PRODUCTS



RAS-LP3

Specifications and dimensions

- 22mm Lamp holder
- Transformer type



Features	
Width	30mm
Depth behind panel	40mm
Depth behind panel inc contact	56mm
Weight	0.1Kg
Input voltage	110V AC
Lamp (BA9) voltage	6V
Transformer rating	1.2VA
Related Products	
Mounting collar (supplied)	RAS-BCBNC
Lamp head	RAS-LP

ⓘ ALL PRODUCTS, PRODUCT SPECIFICATIONS AND DATA ARE SUBJECT TO CHANGE WITHOUT NOTICE.

Information provided in data sheets and/or specifications may vary from actual results in different applications and performance may vary over time. **All products must be installed according to manufacturers instructions.**