EUROPA

Data Sheet
EDS2129-002

This document must be retained for future reference.

It is the responsibility of the person installing the electrical equipment to ensure that the installation meets the requirements of the IET wiring regulations and is therefore 'fit for purpose'. Factors such as correct selection of components, cable sizing, protective devices and Earth bonding are all critical and should be checked prior to full testing and power-up. Any other regulations applicable to the equipment being installed such as the Machinery Directive and current health and safety legislation must also be adhered to.

All connections (including factory made) must be checked for the correct tightness prior to commissioning of the electrical installation.
All connections should also be inspected periodically to ensure correct tightness.

DO NOT USE POWER TOOLS ON THESE PRODUCTS

RAS-LP7

Specifications and dimensions



- 22mm Lamp holder
- Diode & series resistor type

Features	
Width	30mm
Height	40mm
Depth behind panel	42mm
Depth behind panel inc contact	66mm
Weight	0.054Kg
Input voltage	230V
Lamp (BA9) voltage	110V
Related Products	
Mounting collar (supplied)	RAS-FB
Lamp head	RAS-LP
Illuminated pushbutton	RAS-PB13
Illuminated selector switch	RAS-BK12
Twin pushbutton	RAS-PB1534
Contact block NO	RAS-CBNO
Contact block NC	RAS-CBNC

ALL PRODUCTS, PRODUCT SPECIFICATIONS AND DATA ARE SUBJECT TO CHANGE WITHOUT NOTICE.

Information provided in data sheets and/or specifications may vary from actual results in different applications and performance may vary over time**. All products must be installed according to manufacturers instructions.**

Europa House, Airport Way, Luton, Bedfordshire, LU2 9NH
Technical: 01582 692 444 technical@europa-plc.com
www.europa-plc.com